

# MCA 308



## Multi-Channel 8 Channel Power Amplifier With Bridged System

Spec	Model
<b>Input</b>	MCA 308
Input Sensitivity	< 1.0V at 8 Ohms
Input Connector	RCA
Input Impedance	30K ohms (unbalanced)
<b>Output</b>	
Output Power At (<1%T.H.D)	30 W/ch at 4 Ohms 60 W (Bridged)
Output Connector	EUR black
Frequency Response	+/- 3 dB 20 Hz To 40 KHz
T.H.D Distortion	<0.02% at (20 to 20 KHz)
Hum & Noise	< -90 dB (referred to PRO)
<b>General</b>	
Finish	Black (power coat)
Front Mounted	Power ON/OFF Volume Control
Rear Mounted	Stereo/Bridged Switch Signal Link Switch
Crosstalk	< 60 dB At 1KHz
Voltage Gain	30 dB
Damping Factor	>100 (for loads 4 Ohms at 20 to 20KHz)
Power Requirements	480VA 110/120 VAC 50/60 Hz 220/240 VAC 50/60 Hz
Dimension (W*H*D)	44 x 481 x 350 mm
Net Weight	6.0 Kg